

CJX2(LC1-F) Ac Contactor

Application

CJX2(LC1-F) series AC Contactor is applicable to the circuits up to the rated voltage 1000v AC 50Hz or 60Hz, rated current up to 780A for long distance making breaking circuit and frequently starting of controlling motor. It also can be used for the control of distribution circuits of rated current from 200A to 1600A.

Specifications



CJX2-115(LC1-F115)



CJX2-185(LC1-F185)



CJX2-265(LC1-F265)



CJX2-330(LC1-F330)



CJX2-400(LC1-F400)

Type		CJX2-115	CJX2-150	CJX2-185	CJX2-225	CJX2-265
		(LC1-F115)	(LC1-F150)	(LC1-F185)	(LC1-F225)	(LC1-F265)
Rated working current (A)	AC-3	115	150	185	225	265
	AC-1	200	250	275	315	350
Standard power ratings of 3-phase motors AC-3(kw)	220/230V	30	40	55	63	75
	380/400V	55	75	90	110*	132
	415V	59	80	100	110	140
	440V	59	80	100	110	140
	500V	75	90	110	129	160
	660/690V	80	100	110	129	160
	1000V	65	65	100	100	147

Type		CJX2-330	CJX2-400	CJX2-500	CJX2-630	CJX2-780
		(LC1-F330)	(LC1-F400)	(LC1-F500)	(LC1-F630)	(LC1-F780)
Rated working current (A)	AC-3	330	400	500	630	780
	AC-1	400	500	700	1000	1600
Standard power ratings of 3-phase motors AC-3(kw)	220/230V	100	110	147	200	220
	380/400V	160	200	250	335	400
	415V	180	200	280	375	425
	440V	200	250	295	400	425
	500V	200	257	335	400	450
	660/690V	200	280	335	450	475
	1000V	160	185	335	450	450